

Amendments to the Claims

The listing of claims will replace all prior versions, and listings of claims in the application.

1. (currently amended) A method for down-converting an electromagnetic signal, comprising the steps of:

- (1) simultaneously down-converting and performing a matched filtering/correlating operation on a portion of a an initially received carrier signal;
- (2) accumulating the result of the matched filtering/correlating operation of step (1); and
- (3) repeating steps (1) and (2) for additional portions of the carrier signal.

2. (original) The method according to claim 1, wherein step (1) comprises the step of convolving an approximate half cycle of the carrier signal with a representation of itself.

3. (previously presented) The method according to claim 1, wherein step (1) comprises the step of multiplying an approximate half cycle of the carrier signal by itself over a predetermined time interval and integrating over the predetermined time interval.

4. (original) The method according to claim 1, where $S_0(t)$ is an output of the matched filtering/correlating operation, k is a constant, $S_i(t)$ is an approximate half cycle of the carrier signal, and t_0-0 is a predetermined time interval, and wherein step (1) comprises the step of processing an approximate half cycle of the carrier signal in accordance with:

$$S_0(t) = k \int_0^{t_0} S_i^2(t) dt .$$

5. (original) The method according to claim 1, where $S_0(t)$ is an output of the matched filtering/correlating operation, k is a constant, $kS_i(t_0-\tau)$ is an impulse response of a matched filtering/correlating operator, t_0 is a predetermined observation time, $u(\tau)$ is a step function, and $S_i(t-\tau)$ is an approximate half cycle of the carrier signal, and wherein step (1) comprises the step of processing the approximate half cycle of the carrier signal in accordance with:

$$S_0(t) = \int_0^{\infty} \left(kS_i(t_0 - \tau)u(\tau) \right) S_i(t - \tau) d\tau .$$

6. (original) The method according to claim 1, wherein step (2) comprises the step of transferring a portion of the energy contained in an approximate half cycle of the carrier signal to an energy storage device.

7. (original) The method according to claim 1, wherein step (2) comprises the step of transferring a portion of the energy contained in an approximate half cycle of the carrier signal to a capacitive storage device.

8. (original) The method according to claim 1, further comprising the step of:
(4) passing on the accumulation result of step (2) to a reconstruction filter.

9. (original) The method according to claim 1, further comprising the step of:
(4) passing on the accumulation result of step (2) to an interpolation filter.

10. (original) The method according to claim 1, wherein step (3) comprises the step of repeating steps (1) and (2) at a sub-harmonic rate of the carrier signal.

11. (original) The method according to claim 1, wherein step (3) comprises the step of repeating steps (1) and (2) at an off-set of a sub-harmonic rate of the carrier signal.

12. (original) The method according to claim 1, further comprising the step of:
- (4) performing steps (1), (2), and (3) for positive approximate half cycles of the carrier signal and for inverted negative approximate half cycles of the carrier signal.

13-74. (canceled)